

RTL-M Spare Tire Mount Installation Instructions

44-7795



2950 Norman Strasse Rd • San Marcos • CA • 92069

Phone 760-560-2252 • Fax 760-560-0383

info@bajadesigns.com • www.bajadesigns.com

LIMITED LIFETIME WARRANTY

Baja Designs proudly offers a LIFETIME WARRANTY against manufacturer's defect on all of the products that we manufacture.

These are comprehensive warranties; other than the exclusions below – you're covered. If your LED or HID bulb burns out, you're covered. Additionally, cutting off our connector or changing your lenses does not automatically void your warranty.

Exclusions:

Installation errors, abuse, misuse, or crash damage. You must be the original owner of the product and can supply proof of purchase.

Baja Designs manufactures its own products as well as resells products manufactured by others. Baja Designs makes no express or implied warranties on products not manufactured by Baja Designs including without limitation any warranties or merchantability and fitness for a particular purpose. We will, however, pass on all warranties made by the manufacturer, who has sole responsibility for performing such warranties.

Baja Designs will pay the freight if your product is less than 90 days old, otherwise defective products must be returned to Baja Designs, Inc., freight prepaid. At our option, we will repair or replace items in question and return them at no charge. If the identical product is no longer available, we will replace with a similar product of equal value. Baja Designs Inc. will not be responsible for any indirect or consequential damages in connection with defective merchandise.

Items purchased through a Baja Designs authorized dealer must be returned through the dealer. Only available on LED auxiliary lights and product must be in sellable condition at MSRP. Product that has been damaged in any way after the original purchase date will be excluded from this guarantee.

Indemnification:

Buyer hereby acknowledges off-roading, racing and driving at night are dangerous activities and that the products and/or supplies purchased from Baja Designs are used in an inherently dangerous activity that may endanger life and limb; and in no event shall the seller, or seller's heirs and assigns, be held liable for consequential damages, nor shall seller's liability on any claim for damages arising out of or connected with the sale, delivery, or use of purchased products and/or supplies exceed the purchase price of the products and/or supplies.

RTL-M Spare Tire Mount Kit Installation Instructions

- 1.) Remove the two upper lugnuts on the spare tire and install the provided replacement lugnuts with the tapered side towards the wheel and torque to specifications *Figure 1*.



Figure 1

- 2.) Install the provided threaded hex standoffs onto the remaining thread of the upper lugstuds and torque to specifications *Figure 2*.



Figure 2

- 3.) Install the light onto the spare tire mount bracket with 2 provided $\frac{1}{4}$ " bolts, 2 washers and 2 locknuts *Figure 3*.



Figure 3

- 4.) Mount the bracket to the threaded hex standoffs with the provided $\frac{1}{2}$ " bolts, washers and lock washers assembling with the lock washers sandwiched between washer and bolt head *Figure 4*.



Figure 4

- 5.) Mount vehicle's license plate to the lower portion of the bracket with the remaining $\frac{1}{4}$ " bolts, washers and locknuts assembling with two washers sandwiched between license plate and bolt head and the other two between the bracket and locknuts *Figure 5*.



Figure 5

- 6.) Route the light's wiring behind the bracket allowing for manufacturer functionality such as a swing open tire mount being sure to keep wiring away from moving parts.

Wiring Instructions

RTL / RTL-M Wiring Instructions

Black

_____ Ground

Red

_____ Amber / Running

Yellow

_____ Amber / Brake

Blue

_____ White Light

- The RTL is able to run at 9-36 Volts
- Red, yellow, and blue function off positive current
- Yellow(brake) will only function is Red(running) is receiving power
- To run the white light, it is recommended you put it on a switch